

PRODUCT SPECIFICATION

Input voltage	9V to 26V
Extra features	5W
Power supply	5V Camera @ under 180mA
Output power	25/100/200/1000/5000mW
Microphone	Not supported
Antenna connector	SMA
Cable connector	JST, 6pin
Kit contents	1x VTX, 1x cable, 1x pigtail



TX3705

PRODUCT SPECIFICATION

Key features

- 25/100/200/1000/5000mW power switchable
- Built-in cooling fan
- 9-26V input with 5V output

Button control Channel select mode

One button is used to set channel, band and power.

Channel Select

Short press to change 8 channels.

Band Select

Press the button for 2 seconds, LED will flicker an letter and a dot, then short press to change 5 band from A-b-c-d-E

Power Select

Press the button for 3 seconds, LED will flicker an number and a dot, then short press to change 5 power levels.

After setting, led will display letter-number-number and a dot, representing band-channel-power level

For example:



PRODUCT SPECIFICATION

Band	CH1	CH2	CH3	CH4	CH5	CH6	CH7	CH8
Band A	3200	3220	3240	3260	3280	3300	3320	3340
Band b	3360	3380	3400	3420	3440	3460	3480	3500
Band c	3520	3540	3560	3580	3600	3620	3640	3680
Band d	3210	3250	3290	3330	3370	3410	3450	3490
Band E	3230	3290	3350	3410	3470	3530	3590	3700

HOT CAUTION
BE CAREFUL NOT TO BURN YOUR FINGERS

PLUG THE ANTENNA BEFORE POWERING THE VTX
DO NOT REMOVE COOLING FAN